

# SMART ENERGY CONTROLLER

Model: SUN2000-12/15/17/20/25K-MB0



**Active Safety**  
AFCI Active Arcing  
Protection



**Higher Yields**  
Up to 30% More Energy  
with Optimizer <sup>1</sup>



**Battery Ready**  
2 Battery Terminals;  
Compatible with LUNA2000-S0

# SUN2000-12/15/17/20/25K-MB0

## Technical Specification

Technical Specification <sup>1</sup>	SUN2000-12K-MB0	SUN2000-15K-MB0	SUN2000-17K-MB0	SUN2000-20K-MB0	SUN2000-25K-MB0
Efficiency					
Max. efficiency	98.4%	98.4%	98.4%	98.4%	98.4%
European weighted efficiency	97.9%	98.0%	98.1%	98.1%	98.2%
DC Input					
Recommended max. PV power	18,000 Wp	22,500 Wp	22,500 Wp	30,000 Wp	37,500 Wp
Max. input voltage <sup>2</sup>	1,100 V				
Max. input current per MPPT	30 A (two strings) / 20 A (single string)				
Max. short-circuit current	40 A				
Start-up voltage	200 V				
MPPT operating voltage range <sup>3</sup>	200 V-1000 V				
Full-load MPPT voltage range	370 V-800 V	410 V-800 V	440 V-800 V	480 V-800 V	530 V-800 V
Rated input voltage	600 V				
Max. number of inputs	4				
Number of MPP trackers	2				
Smart String Energy Storage System Terminal					
Compatible Smart String ESS	LUNA2000-5/10/15-S0, LUNA2000-7/14/21-S1				
Number of terminals	2				
Max. charging power	21 kW (Single string) / 25 kW (Two strings)				
Max. discharge power	13.2 kW	16.5 kW	18.7 kW	22.0 kW	25.0 kW
Max. operating current	26.25 A (per string)				
Operating voltage range	600 V ~ 980 V				
Output					
Rated output power	12,000 W	15,000 W	17,000 W	20,000 W	25,000 W
Max. apparent power	13,200 VA	16,500 VA	18,700 VA	22,000 VA	27,500 VA
Max. active power (cosφ = 1)	13,200 W	16,500 W	18,700 W	22,000 W	27,500 W
Rated output voltage	220 V AC/380 V AC, 230 V AC/400 Vac, 240 V AC/415 V AC; 3 W/N + PE				
Rated output current	18.2 A/380 V AC	22.8 A/380 V AC	25.8 A/380 V AC	30.4 A/380 V AC	38.0 A/380 V AC
	17.3 A/400 V AC	21.7 A/400 V AC	24.5 A/400 V AC	28.9 A/400 V AC	36.1 A/400 V AC
Max. output current	16.7 A/415 V AC	20.9 A/415 V AC	23.7 A/415 V AC	27.8 A/415 V AC	34.8 A/415 V AC
	20.2 A/380 V AC	25.2 A/380 V AC	28.6 A/380 V AC	33.6 A/380 V AC	42.0 A/380 V AC
	19.1 A/400 V AC	23.9 A/400 V AC	27.1 A/400 V AC	31.9 A/400 V AC	39.9 A/400 V AC
Rated AC grid frequency	50 Hz/60 Hz				
Adjustable power factor	0.8 leading ... 0.8 lagging				
Max. total harmonic distortion	≤ 3%				
Feature & Protection					
Overvoltage category	PV II/AC III				
Input-side disconnection device	Yes				
Anti-islanding protection	Yes				
AC over-current protection	Yes				
DC reverse-polarity protection	Yes				
DC surge protection	TYPE II				
AC surge protection	Yes, compatible with TYPE II protection class according to EN/IEC 61643-11				
DC insulation resistance detection	Yes				
Residual current monitoring unit	Yes				
Arc fault protection	Yes				
General Specification					
Operating temperature range	-25 °C to +60 °C (-13 °F to 140 °F)				
Relative humidity	0 % RH-100 % RH				
Max. operating altitude	4,000 m (13,123 ft.) (Derated above 2,000 m)				
Cooling	Smart air cooling				
Display	LED indicators, Integrated WLAN + FusionSolar APP				
Communication	RS485; WLAN/Ethernet via Smart Dongle-WLAN-FE (Optional) 4G/3G/2G via Smart Dongle-4G (Optional); EMMA (Optional)				
Weight	21 kg				
Dimensions (W x H x D)	546 mm x 460 mm x 228 mm (21.5 x 18.1 x 9.0 inch)				
Protection level	IP66				
Max. number of paralleled unit (with Smart String ESS)	3				
Optimizer Compatibility					
Compatible optimizer	SUN2000-450W-P2, SUN2000-600W-P, MERC-1100W-P, MERC-1300W-P				
Standards Compliance (More Available Upon Request)					
Certificates	EN/IEC62109-1, EN/IEC62109-2				
Grid connection standards	IEC61727, IEC62116, IEC61683, EN50530, ABNT NBR 16149/16150, MEA/PEA, G99, IRR-DCC-MV/IRR-TIC, Philippine Grid Code Resolution No. 07, NRS 097-2-1, EN50549-1, VDE4105, UTE15-712-1/VFR 2019, UNE217002, NTS631, RD244(UNE217001), PPDS, ROGA, TOR Erzeuger, CEI 0-21:2020-12 V1, CEI-016, C10/C11, EN50549-2, VDE4110				

\*1 For Thailand, only SUN2000-12K-MB0 & SUN2000-15K-MB0 & SUN2000-20K-MB0 are available.

\*2 The maximum input voltage is the upper limit of the DC voltage. Any higher input DC voltage would probably damage the inverter.

\*3 Any DC input voltage beyond the operating voltage range may result in inverter malfunction.

Disclaimer: The preceding values are measured by an internal laboratory of Huawei in a specific environment. The actual values may vary with products, software versions, usage conditions, and environmental factors.